

## 3000 & 5000-Watt – Gasoline

### Alternator:

- Total harmonic distortion (THD) less than 5%
- 100% copper windings

### Frame:

- Heavy-duty powder coated wraparound frame with 1-inch steel tubing
- Angled isolator design features four neoprene isolators

### Components:

- Easy-access and protected control panel with magnetic circuit breakers and GFCI-protected receptacles
- Large low tone mufflers
- Fuel shut-off valve
- Easy-to-read fuel gauge
- Heavy-duty industrial air cleaner

### Miscellaneous:

- USDA/USFS-approved spark arrestors

### Limited Warranties:


- 2 year alternator
- 3 year Honda and Kohler engines

### Certification:

- CSA Certified



GEN-3000-1MK0



Perfect for powering a multitude of tools on any jobsite, the 3000-watt and 5000-watt generators were designed with contractors in mind. And, the long run times mean you don't have to take a refuel break.

| MODEL NO.               | GEN-3000-1MH0             | GEN-3000-1MK0             | GEN-5000-0MH0  | GEN-5000-0MK0  |
|-------------------------|---------------------------|---------------------------|--|--|
| MAX. AC OUTPUT          | 3000 watts                | 3000 watts                | 5000 watts   | 5000 watts   |
| RATED AC OUTPUT         | 2450 watts                | 2450 watts                | 4400 watts   | 4400 watts   |
| DISPLACEMENT/ENGINE     | 163cc Honda GX160 OHV     | 208cc Kohler CH270 OHV    | 270cc Honda GX270 OHV  | 277cc Kohler CH395 OHV   |
| ALTERNATOR              | Brushless 120V, 60Hz      | Brushless 120V, 60Hz      | Brushless 120V/240V, 60Hz  | Brushless 120V/240V, 60Hz  |
| MAX. AMPS (120V/240V)   | 25.0                      | 25.0                      | 41.7/20.8  | 41.7/20.8  |
| CONT. AMPS (120V/240V)  | 20.4                      | 20.4                      | 36.7/18.3  | 36.7/18.3  |
| RECEPTACLES             | (1) 120V, 20A GFCI duplex | (1) 120V, 20A GFCI duplex | (2) 120V, 20A GFCI duplex<br>(1) 120V/240V, 20A twist lock<br>(1) 120V, 30A twist lock   | (2) 120V, 20A GFCI duplex<br>(1) 120V/240V, 20A twist lock<br>(1) 120V, 30A twist lock   |
| CIRCUIT BREAKERS        | (1) 20A push-button       | (1) 20A push-button       | (2) 20A toggle circuit breakers, single pole<br>(1) 20A toggle circuit breaker, double pole<br>(1) 30A toggle circuit breaker, single pole | (2) 20A toggle circuit breakers, single pole<br>(1) 20A toggle circuit breaker, double pole<br>(1) 30A toggle circuit breaker, single pole |
| RATED SPEED             | 3600 RPM                  | 3600 RPM                  | 3600 RPM   | 3600 RPM   |
| DECIBEL RATING          | 74.8                      | 74.8                      | 73.8   | 73.8   |
| FUEL CAPACITY           | 2.6 gallons               | 2.6 gallons               | 5.7 gallons  | 5.7 gallons  |
| RUN TIME (AT FULL LOAD) | 7.4 hours                 | 7.4 hours                 | 6.8 hours  | 6.8 hours  |
| FULL POWER SWITCH       | No                        | No                        | Yes  | Yes  |
| DIMENSIONS (LxWxH)      | 25x18x18in.               | 25x18x18in.               | 29x19.75x22.5in.   | 29x19.75x22.5in.   |
| SHIP WT.                | 146 lb.                   | 146 lb.                   | 198 lb.  | 198 lb.  |
| NET WT.                 | 130 lb.                   | 130 lb.                   | 176 lb.  | 176 lb.  |

Noise level tested at seven meters (75% load). Rating represents minimum noise level rating.

### Accessories & Options:

| PART NUMBER  | DESCRIPTION          | FITS MODELS      | PART NUMBER  | DESCRIPTION                    | FITS MODELS      |
|--------------|----------------------|------------------|--------------|--------------------------------|------------------|
| 32-0915      | RV generator adapter | 5000-watt models | AW-5740-0009 | Wheel kit with flat-free tires | 5000-watt models |
| AW-5090-0003 | Lifting hook         | 5000-watt models | GX-0004      | Hour meter                     | 5000-watt models |