

# **Stationary All-Electric**

Dealer Hot Water Pressure Washers



DHA Series - Belt Drive



The DHA Series is all-electric and features a patented heat exchanger design to provide consistent and efficient hot water on-demand.

### PUMP

- · Forged brass manifold
- · Stainless-steel and brass unloader valve
- Factory preset unloader
- Thermal relief valve

### MOTOR

- Open drip-proof electric motor with manual thermal overload protection
- On/off power switch

### FRAME

· Stainless-steel base and frame with rubber isolators

### COMPONENT

· Time delay shutdown

### UNIT INCLUDES

- Quick connect nozzles 0°, 15°, 25° and 40°
- External downstream detergent injector with detergent nozzle
- 50-foot x  $\%\mbox{-inch-inch}$  steel wire-braided high pressure black hose
- Adjustable pressure insulated dual lance with trigger gun

### **HEAT EXCHANGER**

- · Patented cartridge design
- · Used for consistent and efficient on-demand hot water
- 120°F to 130°F temperature rise above in-take water, obtained within 3 to 5 minutes
- Adjustable thermostat
- On/Off power switch
- Powder coated steel frame
- Low maintenance, stainless-steel coils in aluminum casings for maximum efficiency
- · Eliminates constant cleaning and heat loss

## LIMITED WARRANTIES

• 1 year electric motor

### **CERTIFICATION**

ETL certified – US and Canada



## Stationary All-Electric Hot Water – DHA Series – Belt Drive

MODEL NUMBER	PSI	GPM	HORSEPOWER/ MOTOR	UNIT AMPERAGE	PUMP	HEATER kW	TEMPERATURE RISE	DIMENSIONS (LxWxH)	SHIP WT.	NET WT.
DH-2503-AE0E4G	2500	2.8	6.0 HP, 480V, 3Ø	68.0A	General	48	120°F	36x25x49in.	725 lb.	625 lb.
DH-3004-AE0E4G	3000	3.9	8.0 HP, 480V, 3Ø	100.0A	General	72	130°F	36x25x49in.	830 lb.	725 lb.

### **OPTIONS:**

PART NUMBER	DESCRIPTION	FITS MODELS
HX-0298	Remote box – Adds control box, may be mounted away from unit to control on/off, controls the hot water heater and cold water pump	All models
HX-0307	Auto start/stop - When trigger gun is released, the timer will turn unit off; when trigger gun is pulled, unit will restart	All models



